




































Accessory Compatibility Chart

		Garage Door Opener Manufacture Year	1993-1995	1996-2005	2006-2014	2011+		
		Learn Button Color	 Billion Code	 Security+®	 Security+	 Security+ 2.0®		
		Frequency Code	390MHZ	390MHZ	315MHZ	310, 315, 390MHZ		
		Model Numbers	1245/1255, 1270/1280	1245R/1255R, 1265R, 2220, 2245/2255, 2265, 2280, 2500, 2575, 2585, 2595	1345/1355, 1356, 3220, 3255, 3240, 3265, 3270, 3280, 3800, 3500, 3850, 3585, 3595	8065, 8155, 8165, 8355, 8360, 8365-267, 8500, 8550, 8557, 8587		
Remote Controls	Pack - in						Features	
375UT	2-Button Universal Remote Control	No		X	X	X	X	<ul style="list-style-type: none"> - Compatible with most major brands of Garage Door Openers, Gate Operators and Commercial Door Operators. - Program and control up to two different brands of Garage Door Openers.
895MAX	3-Button Elite Remote Control	Elite Series® Models 8500, 8587, 8557, 8550		X	X	X	X	<ul style="list-style-type: none"> - Compatible with all Garage Door Openers manufactured by LiftMaster® since January 1993. - Program and control up to three Garage Door Openers, Gate Operators, Commercial Door Operators or MyQ® Light Accessories. - Bright blue LED buttons make night operation easy.
893MAX	3-Button Remote Control	No		X	X	X	X	<ul style="list-style-type: none"> - Compatible with all Garage Door Openers manufactured by LiftMaster since January 1993. - Program and control up to three Garage Door Openers, Gate Operators, Commercial Door Operators or MyQ Light Accessories. - Different size buttons for quick and easy activation.
890MAX	3-Button Mini Remote Control	No		X	X	X	X	<ul style="list-style-type: none"> - Compatible with all Garage Door Openers manufactured by LiftMaster since January 1993. - Program and control up to three Garage Door Openers, Gate Operators, Commercial Door Operators or MyQ Light Accessories. - Fits on a keychain, or in a purse or pocket.
893LM	3-Button Remote Control	Premium Series Models 8360, 8355, 8365-267					X	<ul style="list-style-type: none"> - Compatible with LiftMaster Security+ 2.0® Garage Door Openers, Gate Operators, and Commercial Door Operators. - Program and control up to three Garage Door Openers, Gate Operators, Commercial Door Operators or MyQ Light Accessories. - With Security+ 2.0 Rolling Code Technology, users are assured of a new code with every use. - Different size buttons for quick and easy activation.
891LM	1-Button Remote Control	Contractor Series Models 8065, 8155, 8165					X	<ul style="list-style-type: none"> - Compatible with a single LiftMaster Security+ 2.0 Garage Door Opener, Gate Operator and Commercial Door Operator. - Program and control a single Garage Door Opener, Gate Operator, Commercial Door Operator or MyQ Light Accessories. - With Security+ 2.0 Rolling Code Technology, users are assured of a new code with every use. - Large single button for quick and easy activation.
373LM	3-Button Remote Control	Premium Series Model 3240				X		<ul style="list-style-type: none"> - Compatible with LiftMaster Security+ 315 MHz Garage Door Openers, Gate Operators and Commercial Door Operators. - Program and control up to three Garage Door Openers, Gate Operators or Commercial Door Operators. - With Security+ Rolling Code Technology, users are assured of a new code with every use. - Different size buttons for quick and easy activation.
371LM	1-Button Remote Control	No				X		<ul style="list-style-type: none"> - Compatible with LiftMaster Security+ 315 MHz Garage Door Openers, Gate Operators and Commercial Door Operators. - Program and control a single Garage Door Opener, Gate Operator or Commercial Door Operator. - With Security+ Rolling Code Technology, users are assured of a new code with every use. - Large single button for quick and easy activation.
Keypads								
387LM	Universal Wireless Keyless Entry	No		X	X	X	X	<ul style="list-style-type: none"> - Compatible with most major brands of Garage Door Openers. - Open or close the garage door without using a remote control or key. - Users can also program a temporary code for friends and service people.
877MAX	Wireless Keyless Entry	No		X	X	X	X	<ul style="list-style-type: none"> - Compatible with all Garage Door Openers manufactured by LiftMaster since January 1993. - Open or close the garage door without using a remote control or key. - Users can also program a temporary code for friends and service people. - Closes the garage door instantly with one press activation.
877LM	Wireless Keyless Entry	Premium Series Model 8365-267					X	<ul style="list-style-type: none"> - Compatible with all Garage Door Openers manufactured by LiftMaster since January 1993. - Open or close the garage door without using a remote control or key. - Users can also program a temporary code for friends and service people. - Closes the garage door instantly with one press activation.
377LM	Wireless Keyless Entry	No				X		<ul style="list-style-type: none"> - Compatible with LiftMaster Security+ 315 MHz Garage Door Openers. - Open or close the garage door without using a remote control or key. - Users can control up to four Garage Door Openers and program a temporary code for friends and service people. - Closes the garage instantly with one press activation.

Garage Door Opener Manufacture Year Learn Button Color Frequency Code Model Numbers			1993-1995	1996-2005	2006-2014	2011+	Features
Control Panels	Pack - in		 Billion Code 390MHZ 1245/1255, 1270/1280	 Security+® 390MHZ 1245R/1255R, 1265R, 2220, 2245/2255, 2265,2280, 2500, 2575,2585,2595	 Security+ 315MHZ 1345/1355, 1356, 3220, 3255, 3240, 3265, 3270, 3280, 3800, 3500, 3850, 3585, 3595	 Security+ 2.0® 310, 315, 390MHZ 8065, 8155, 8165, 8355, 8360, 8365-267, 8500, 8550, 8557, 8587	
888LM	MyQ® Control Panel	Elite Series® Model 8500		X*	X		<ul style="list-style-type: none"> *Allows most LiftMaster® Garage Door Openers manufactured since 1998 to be controlled by a smartphone, tablet or computer—when paired with the Internet Gateway 828LM. Provides the upgrade needed to utilize Security+ 2.0® and MyQ Technology. Equipped with Timer-to-Close feature, which automatically closes the garage door after a pre-programmed number of minutes. Motion detector activates the Garage Door Opener lights as soon as movement is detected. Lock button blocks the garage door from being opened by remote controls.
880LM	Smart Control Panel®	Elite Series Models 8550, 8587, 8557				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Garage Door Openers. Equipped with Timer-to-Close feature, which automatically closes the garage door after a pre-programmed number of minutes. Includes time and temperature on LCD panel and maintenance alerts. Motion detector activates the Garage Door Opener lights as soon as movement is detected. Lock button blocks the garage door from being opened by remote controls.
881LM	Motion-Detecting Control Panel w/ Timer-to-Close	No				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Garage Door Openers. Motion detector activates the Garage Door Opener lights as soon as movement is detected. Equipped with Timer-to-Close feature, which automatically closes the garage door after a pre-programmed number of minutes. Includes Maintenance Alert System.
885LM	Wireless Control Panel	No				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Garage Door Openers. Controls one Garage Door Opener and lights. Powered by (1) 3 - volt battery (included).
886LM	Motion-Detecting Control Panel	Premium Series Model 8360				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Garage Door Openers. Automatically turns on the light when motion is detected. Includes Garage Door Opener light control, lockout remote controls for added security and Maintenance Alert System.
882LM	Multi-Function Control Panel	Premium Series Models 8355, 8365-267 and Contractor Series Models 8155, 8165				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Garage Door Openers. Program remote controls, keypads and MyQ Light Accessories from the control panel. Includes display lights, Garage Door Opener light control, and lockout remote controls for added security.
378LM	Wireless Secondary Control Panel	No			X		<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 315 MHz Garage Door Openers. Program up to two Garage Door Openers wirelessly and can be installed anywhere in the garage. Controls Garage Door Opener and can turn opener light on and off.
78LM	Multi-Function Control Panel	Premium Series Model 3240		X	X	X	<ul style="list-style-type: none"> Compatible with all Garage Door Openers manufactured by LiftMaster since 1993. Turn Garage Door Opener lights on and off from inside the garage. Includes adjustable light timer, illuminated push button for convenience, and lockout button for added security.
883LM	Door Control Button	Contractor Series Models 8065				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Garage Door Openers. Easily program remote controls, keypad, and MyQ Light Accessories from the control panel. Controls one Garage Door Opener and turns lights on and off.
MyQ Accessories							
821LM	MyQ Garage	No		X	X	X	<ul style="list-style-type: none"> Compatible with most major brands of Garage Door Openers with photo eyes. Monitor and control the garage door and control home lighting from a smartphone, tablet or computer. MyQ mobile app sends alerts that can be received as email or pop-up (push) notifications on a mobile device so that the status of the garage door and houselights is always known.
828LM	Internet Gateway	No				X	<ul style="list-style-type: none"> Connects MyQ-Enabled Garage Door Openers and Accessories to the Internet. MyQ mobile app sends alerts that can be received as email or pop-up (push) notifications on a mobile device so that the status of the garage door and houselights is always known. Open and close the garage door or gate from anywhere and control houselights with a smartphone, tablet or computer.
MYQPCK	MyQ Retrofit Package LiftMaster Openers 1998-2012, Includes 1-888LM and 1-828LM	No			X	X	<ul style="list-style-type: none"> Includes (1) MyQ Control Panel 888LM and (1) Internet Gateway 828LM. Allows any LiftMaster Garage Door Opener manufactured since 1998 to be controlled by a smartphone, tablet or computer—when paired with the Internet Gateway 828LM. Provides the upgrade needed to utilize Security+ 2.0 and MyQ Technology.
829LM	Door and Gate Monitor	No				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Garage Door Openers, Gate Operators and MyQ Light Accessories. Monitor and close up to four garage doors or gates from any room inside the house. Compatible with the MyQ Control Panel 888LM.
823LM	Remote Light Switch	No				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Remote Controls. Replaces the existing wall switch in order to control home lighting with a smartphone or Garage Door Opener remote control. Requires Internet Gateway 828LM or MyQ Garage 821LM for smartphone control.
825LM	Remote Light Control	No				X	<ul style="list-style-type: none"> Compatible with LiftMaster Security+ 2.0 Remote Controls. Control any lamp with a Garage Door Opener remote control, smartphone, tablet or computer via the Internet Gateway 828LM or MyQ Garage 821LM.